





12		C shell	1	
11		key	1	
10		Battery	1	
9		Lens	1	
8		S shell	1	
7		key	1	
6		Loudspeaker	1	
5		Mainboard	1	
4		display	1	
3		key	1	
2		A shell	1	
1		lens	1	
S/N	Q	PH	Qty	RS

CL8600


CL8600 Service Part List			
Item	Description	Unit	Price
1	CL8600 E19 battery	1	Please contact our helpline
2	CL8600 rear-facing camera assembly	1	Please contact our helpline
3	CL8600 external charging port(s)	1	Please contact our helpline
4	CL8600 mechanical button(s)	1	Please contact our helpline
5	CL8600 main microphone(s)	1	Please contact our helpline
6	CL8600 speaker(s)	1	Please contact our helpline
7	CL8600 mechanical display folding mechanism	1	Please contact our helpline

REVISION RECORD			
LTR	ECO NO.	APPROVED	DATE


PMU_ANALOG



BKBT



RTC




RTC Mode	R0204	R0203	X0200	C0201	C0202	R0202	R0214
32K Crystal	NF	OR	Crystal	8.2pF	8.2pF	OR	NF
32K-less	10K	NF	NF	NF	NF	NF	OR

COMPANY: GEEMARC TELECOM			
TITLE:			
DRAWN:	DATED:	CODE:	SIZE:
CHECKED:	DATED:	DRAWING NO.	
QUALITY CONTROL:	DATED:	REV:	
RELEASED:	DATED:	SCALE:	
SHEET: 1 of 12			

REVISION RECORD			
LTN	ECO NO.	APPROVED	DATE

PMU_POWER



SC2720 DCDC output

Input Power	Power Name	Output Voltage (V)	Output Current	Default Voltage	Default
VBAT	DCDCCORE	0.4-1.4	3500mA	0.9V	ON
	DCDCGEN1V8	1.6-2.1	2000mA	1.85V	ON
	DCDCWPA	0.4-3.4 2x and 2.5x ramp	1000mA		OFF


SC2720 LDO output

Input Power	Power Name	Output Voltage (V)	Output Current	Default Voltage	Default
LDO from VBAT	VDDCAMA	1.8-3.3	150mA	2.8V	OFF
	VDDCMMOT	1.8-3.3	100mA	2.8V	OFF
	VDDSIM0	1.8-3.3	50mA		OFF
	VDDSIM1	1.8-3.3	50mA		OFF
	VDDSIM2	1.8-3.3	200mA		OFF
	VDDMMCCORE	1.8-3.3	400mA	3.0V	ON
	VDDSD	1.8-3.3	400mA	3.0V	ON
	VDDSDIO	1.8-3.3	400mA	3.0V	ON
	VDD28	1.8-3.3	100mA	2.8V	ON
	VBATBK	1.8-3.3	10mA	3.0V	ON
	VDDVIB	1.8-3.3	100mA		OFF
	VDDKPLED	1.8-3.3	50mA		OFF
	VDDWIFIPA	1.8-3.3	400mA	3.3V	OFF
	VDDDCXO	1.8-3.3	20mA	1.8V	ON
	VDDUSB33	1.8-3.3	60mA	3.3V	ON
LDO from DCDCGEN	VDD_MEM	1.0-1.8	800mA	1.2V	ON
	VDDCAMD	1.0-1.8	400mA	1.25V	OFF
	VDDRFB	1.2-1.8	50mA	1.8V	OFF
	VDD_CON	1.0-1.8	200mA	1.2V	OFF
	VDDCAMIO	1.2-1.8	200mA	1.8V	OFF
	AVDD18	1.2-1.8	100mA	1.8V	ON
	VDDRFA	1.2-1.8	200mA	1.8V	ON


COMPANY: GEEMARC TELECOM			
TITLE:			
DRAWN:	DATED:	CODE:	SIZE:
CHECKED:	DATED:	DRAWING NO.	
QUALITY CONTROL:	DATED:	REV:	
RELEASED:	DATED:	SCALE:	
		SHEET: 2 of 12	

REVISION RECORD			
LTR	ECO NO:	APPROVED:	DATE:


Primary Antenna




Ant tunner




TDD B34/B39/GSM PA + Switch




PCS1900




GSM850




FDDLTE/WCDMA_B1




FDDLTE/WCDMA_B2




FDDLTE_B3




FDDLTE/WCDMA_B5




FDDLTE_B7




FDDLTE/WCDMA_B8




FDD_B20



FDD_B28B





FDD_B28A



		COMPANY: GEEMARC TELECOM			
		TITLE:			
DRAWN:	DATED:				
CHECKED:	DATED:	CODE:	SIZE:	DRAWING NO:	REV:
QUALITY CONTROL:	DATED:				
RELEASED:	DATED:	SCALE:			SHEET: 5 OF 12

REVISION RECORD			
LTR	ECO NO.	APPROVED:	DATE

Diversity LTE Path



COMPANY: GEEMARC TELECOM			
TITLE:			
DRAWN:	DATED:	CODE:	SIZE:
CHECKED:	DATED:	DRAWING NO.	REV:
QUALITY CONTROL:	DATED:		
RELEASED:	DATED:		
SCALE:			SHEET: 6 OF 12


REVISION RECORD			
LTH	ECO NO.	APPROVED	DATE

FLASH_LED

LCM


TF CARD

KEYPAD LED




should afford 50mA current
Support 2 mode, Choose any one, and then delete ohm select resistor


VIB




2M MAIN CAM




SIDE_KEY




SIM0 & SIM1




SOS



TYPE-C




Test Points




MARK POINT

Battery temperature monitor




R6101 use 0402 for EOS





		COMPANY: GEEMARC TELECOM			
		TITLE:			
DRAWN:	DATED:				
CHECKED:	DATED:	CODE:	SIZE:	DRAWING NO:	REV:
QUALITY CONTROL:	DATED:				
RELEASED:	DATED:				
		SCALE:		SHEET: 10 of 12	

REVISION RECORD			
LTH	ECO NO.	APPROVED	DATE

WIFI&BT&GPS ANT




Default SC2332B without GPS Backup SC2342B with GPS





GND


WIFI/BT SAW



GE2 FOR BACKUP



GPS SAW LNA



Wide supply voltage range:1.6V-2.8V
2uA when EN=Low
8mA when EN=High


SC2332B&NA VS SC2342B&GPS

Type	U7201	R7227	R7213	R7204	R7247	FB7201	U7203	U7202
DCXO Solution for SC2332B	SC2332B	NF	NF	NF	NF	NF	NF	10K
TSX Solution for SC2342B	SC2342B	OR	OR	OR	OR	OR	SMT	SMT



COMPANY: GEEMARC TELECOM			
TITLE:			
DRAWN:	DATED:		
CHECKED:	DATED:		
QUALITY CONTROL:	DATED:		
RELEASED:	DATED:		
CODE:	SIZE:	DRAWING NO.	REV:
SCALE:		SHEET: 11 of 12	

REVISION RECORD			
LTR	ECO NO:	APPROVED:	DATE:


WIFI





GPS




COMPANY: GEEMARC TELECOM			
TITLE:			
CODE:	SIZE:	DRAWING NO:	REV:
SCALE:	SHEET: 12 of 12		














Troubleshooting

Fault analysis:

Can't turn on:

- 1, Upgrade the motherboard
- 2, Bad motherboard replacement
- 3, Bad battery replacement

Abnormal Display:

- 1, Bad display screen replacement
- 2, Replace the faulty FPC shaft
- 3, Bad motherboard replacement

No charging

- 1, Try with another power supply and cable.
- 2, Bad battery replacement
- 3, Bad motherboard replacement

No ringtone

- 1, bad speaker replacement
- 2, Bad motherboard replacement

No signal / Poor signal

- 1, Replace the Bad antenna
- 2, Bad motherboard replacement

Camera abnormal

- 1, Bad camera replacement
- 2, Bad motherboard replacement