



FEATURES OF THE AMPLICALL 100

- Loud electronic ringer: **up to 90dB**
- Adjustable volume
- 32 different melodies
- Visual ring indicator
- 3 alarm settings:
 - Flash + Alarm (+ option to add additional shaker)
 - Flash (+ option to add additional shaker)
 - Alarm (+ option to add additional shaker)
- Can be paired with up to 6 transmitters, each having their own zone icon on the base
- Distance between the AMPLICALL 101 ringer and the AMPLICALL100 base: 30 meters. The distance achieved indoors can vary.
- Flashing light indicators for the battery levels of the main base and the other transmitters
- Relay output and door opening duration control setting (2 or 5 seconds)
- AMPLICALL 101 doorbell included

TECHNICAL SPECIFICATIONS OF THE AMPLICALL 100

- Wall and desk mountable
- Frequency: 868MHz
- Operates plugged into the mains supply
- Can work on batteries in the event of a power failure, the same goes for the vibrating pad available in option (3 x AR14 batteries not included)
- Dimensions: 14.6 x 17.6 x 5.5cm

FEATURES OF THE AMPLICALL 101 DOORBELL

- Doorbell for the AMPLICALL 100 and 150
- Ring light around the button
- Wall mountable

TECHNICAL SPECIFICATIONS OF THE AMPLICALL 101 DOORBELL

- Works on 3V CR2032 batteries (included)
- Low battery alert signal
- Frequency: 868MHz
- Dimensions: 3,1 x 7,3 x 2,1 cm

OPTIONAL EXTRAS

- Vibrating Pad (CLA2)
- CLA2 EX

COMPATIBLE PRODUCTS

- AMPLICALL 101 additional doorbell
- AMPLICALL 110, AMPLICALL 140, AMPLICALL150